

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) Publication number: **0 293 189 B1**

(12)

EUROPEAN PATENT SPECIFICATION

(45) Date of publication of patent specification: **13.07.94** (51) Int. Cl.⁵: **H04N 7/13**

(21) Application number: **88304747.4**

(22) Date of filing: **25.05.88**

(54) **High efficiency coding apparatus.**

(30) Priority: **29.05.87 JP 133924/87**

(43) Date of publication of application:
30.11.88 Bulletin 88/48

(45) Publication of the grant of the patent:
13.07.94 Bulletin 94/28

(84) Designated Contracting States:
AT DE FR GB NL

(56) References cited:
EP-A- 0 185 533
EP-A- 0 222 592

(73) Proprietor: **SONY CORPORATION**
7-35 Kitashinagawa 6-chome
Shinagawa-ku
Tokyo 141(JP)

(72) Inventor: **Kondo, Tetsujiro**
c/o Sony Corporation
7-35 Kitashinagawa 6-chome
Shinagawa-ku Tokyo(JP)
Inventor: **Fujimori, Yasuhiro**
c/o Sony Corporation
7-35 Kitashinagawa 6-chome
Shinagawa-ku Tokyo(JP)

(74) Representative: **Ayers, Martyn Lewis Stanley**
et al
J.A. KEMP & CO.
14 South Square
Gray's Inn
London WC1R 6LX (GB)

Note: Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid (Art. 99(1) European patent convention).

EP 0 293 189 B1

Description

The invention relates to a high efficiency coding apparatus applied to a picture signal and, more particularly, to a high efficiency coding apparatus applicable to the case where the transmission rate of recorded data is limited to a predetermined value corresponding to the capacity of a transmission path such as a digital video signal is recorded on a magnetic tape.

The present applicant has proposed a high efficiency coding apparatus for obtaining a dynamic range equal to the difference between a maximum value and a minimum value of plural picture elements contained in a two-dimensional block and for performing the coding adaptive to the dynamic range as described in the specification of the Japanese Patent Application No. 266407/1984 (Publication No. 144989/86). Further, as described in the specification of the Japanese Patent Application No. 232789/1985 (Publication No. 92620/87), a high efficiency coding apparatus for the coding adaptive to a dynamic range with respect to a three-dimensional block formed of picture elements of areas respectively contained in plural frames. Moreover, a variable-length coding method for varying the bit number depending on a dynamic range so as to keep constant the maximum distortion occurring at the time of quantization has been proposed in the specification of the Japanese Patent Application 268817/1985 (Publication No. 128621/87).

The above-mentioned high efficiency coding adaptive to the dynamic range (called "ADRC"), enables great compression of data amount to be transmitted and is therefore suited to the application to a digital VTR. Particularly, the variable-length ADRC can enhance the compression rate. However, since in the variable-length ADRC, the data amount to be transmitted varies depending on the contents of pictures, buffering processing is necessary when a transmission path with a fixed rate such as a digital VTR for recording a predetermined data amount as one track is employed.

For a buffering system of the variable-length ADRC, as described in the Japanese Patent Application No. 257586/1986 (Publication No. 111781/88), the present applicant has proposed the one in which distribution of cumulative-type dynamic ranges is formed, a set of threshold values prepared in advance are applied to the distribution, the amount of data generated in a predetermined period, for instance, in one frame period is obtained, and the generated data amount is controlled so as not to exceed a target value.

Fig. 10 shows a graph of cumulative-type distribution shown in the above-mentioned application. An abscissa of Fig. 10 is a dynamic range, and an

ordinate is a number of occurrence. T1 to T4 depicted in the abscissa are threshold values. The bit number of quantization is determined by the threshold values T1 to T4. In the case of the dynamic range DR within the range of (a maximum value to T1), the bit number of quantization is made to 4; in the case of the range of (T1 - 1 to T2), the bit number of the quantization is made to 3; in the case of the range of (T2 - 1 to T3), the bit number of quantization is made to 2; in the case of the range of (T3 - 1 to T4), the bit number of quantization is made to 1; and in the case of the range of T4 - 1 to a minimum value, the bit number of quantization is made to zero (no code signal is transmitted).

With respect to the cumulative-type distribution, the occurrence numbers ranging from the threshold value (T1 - 1) to the threshold value T2 are accumulated with regard to the occurrence numbers of dynamic ranges from the maximum value to the threshold value T1 in order to obtain distribution of the dynamic range DR in a frame period. The occurrence numbers from the threshold value (T2 - 1) to the threshold value T3 are accumulated similarly. Similar processing is repeated thereafter. As a result, the occurrence number y at which the dynamic range DR is the minimum value is equal to the total number (MxN) of the blocks contained in one frame.

In this manner, when cumulative-type distribution is formed, the cumulative number up to the threshold value T1 becomes x_1 , the cumulative number up to the threshold value T2 becomes $(x_1 + x_2)$, the cumulative number up to the threshold value T3 becomes $(x_1 + x_2 + x_3)$, and the cumulative number up to the threshold value T4 becomes $(x_1 + x_2 + x_3 + x_4)$. As a result, the amount of generated information (total bit number) for a period of one frame is shown by the following equation:

$$4(x_1 - 0) + 3[(x_1 + x_2) - x_1] + 2[(x_1 + x_2 + x_3) - (x_1 + x_2)] + 1[(x_1 + x_2 + x_3 + x_4) - (x_1 + x_2 + x_3)] = 4x_1 + 3x_2 + 2x_3 + x_4.$$

The threshold values T1 to T4 are selected so that the above-mentioned amount of generated information does not exceed a target value. When an optimum value is obtained with the alteration of the threshold values, said values x_1 to x_4 are changed depending on the threshold values, and the calculation of the generated information amount is made for every set of each threshold value. Therefore, once a cumulative-type distribution table is formed, the calculation of generated information can be made easily.

A system for converging the rate of transmission data into a target value by changing the four

threshold values in the level direction, for instance, as mentioned above, is not sufficient in performance such as the reduction of distortion of quantization noises, etc.

An object of the invention is, therefore, to provide a high efficiency coding apparatus capable of achieving buffering processing of transmission data while suppressing the deterioration of the quality of reproduced pictures by changing threshold values for frame-dropping processing in the time direction as well as by changing threshold values in the level direction.

According to the present invention, there is provided a high efficiency coding apparatus for coding digital video data in a format composed of blocks of digital video data representing a three-dimensional group of picture elements belonging to a plurality of frames and for allowing video data compression for transmission by data transmission means having a predetermined transmission capacity, said apparatus comprising:

first and second detecting means for detecting maximum and minimum values, respectively, of the digital video data representing the plural picture elements in each of said blocks;

means for generating dynamic range information for each said block from said maximum and minimum values for the respective block;

movement detecting means for detecting the amount of movement in each block and for generating a detected amount of movement;

means for generating distribution tables addressed by said dynamic range information and said detected movement amount by, for each block into which a predetermined period of not less than one frame period is divided adding a first number to respective entries in said tables if said detected movement amount is greater than a predetermined movement amount and by adding a second number, less than said first number to respective entries in said tables if said detected movement amount is smaller than said predetermined movement amount;

means for determining an encoding bit number for each block and a threshold value of said movement amount during said predetermined period from said distribution tables and said predetermined transmission capacity of said transmission means;

means for averaging digital data of plural video fields in a block in which said detected amount of movement is less than said threshold value to produce a two dimensional block;

encoding means for encoding the digital video data using a number of bits equal to said encoding bit number for each datum in a block; and

means for transmitting the output of said encoding means, a first additional code for each

block formed of at least two of said maximum value, minimum value and a signal based on said dynamic range information and a signal based on the detected amount of movement, and a second additional code for each said predetermined period.

In a high efficiency coding apparatus of the present invention for performing the control so that the amount of generated information does not exceed a transmission capacity of a transmission path when the high efficiency coding is executed, a picture is divided into a number of three-dimensional blocks. The maximum values and minimum values of picture element data contained in each block and dynamic ranges are provided. Also, a movement amount (for instance, a maximum frame difference ΔF) is detected from picture element data different in time from one another and included in the same block. In a still block having a little amount of this movement, the amount of generated information is reduced by frame-dropping processing.

In the frame-dropping processing, a dynamic range DR2, which is the result of the averaging operation, is lowered as compared with a dynamic range DR3 for which no averaging operation is done. For this reason, the position of a still block at an occurrence number block table becomes dynamic range DR2 lower in level than the original dynamic range DR3. This means a reduction of the amount of generated information. As a result, to obtain the amount of generated information, distribution tables on the two dynamic ranges DR3 and DR2 must be prepared. In the case of a block with the dynamic range DR2, the occurrence number of (+1), for example, is given for a value equal to or more than ($\Delta F + 1$) with respect to a maximum frame difference ΔF as a movement amount. In the case of the dynamic range DR3, the occurrence number of (+2), for example, is given for the range of (0 to F) with respect to the maximum difference ΔF . In other words, the occurrence number of (+2) is allotted for the range where a block is handled as a moving one at the time of decision, while the occurrence number of (+1) is allotted for the range where a block is handled as a still one. The distribution tables are converted into cumulative-type distribution tables for every amount of a movement.

By the use of the cumulative-type distribution tables, threshold values and movement threshold values in the level direction are determined so that the amount of generated information does not exceed a target value. Decision on whether the frame-dropping processing is made is done by the movement threshold values. Also, variable-length coding, for example, the word length in the ADRC is controlled by the threshold values in the level direction. Coded data obtained by the variable-

length ADRC is recorded onto a magnetic tape.

Since a movement threshold value for giving a reference of decision on whether the processing of frame dropping should be performed is changed in this invention, excellent buffering which cannot be achieved only with the change in the level direction, can be performed.

Also, in the case where the amount of generated information is obtained, the difference in dynamic range between a still block subjected to frame dropping and a moving block is taken into account. As a result, the amount of generated information can be obtained with high accuracy.

The invention will be more apparent from the following detailed description when taken in conjunction with the accompanying drawings, in which:

Fig. 1 is a block diagram showing a structure on the recording side of one embodiment of the invention;

Figs. 2, 3 and 4 are schematic diagrams for describing a block construction;

Fig. 5 is a block diagram of one example of an ADRC encoder;

Figs. 6 and 7 are schematic diagrams for describing schematic diagrams for describing distribution tables;

Fig. 8 is a block diagram of an example of a three-dimensional distribution generator and a threshold-value determination circuit;

Fig. 9 is a block diagram of one example of an address controller of Fig. 8; and

Fig. 10 is a schematic diagram for explaining a buffering circuit proposed before.

In the entire drawings, the same reference numerals denote the same structural elements.

An embodiment of the invention will be described hereunder referring to the drawings. Description will be given in the order mentioned below.

- a. Structure on the recording side
- b. ADRC encoder
- c. Forming a three-dimensional distribution table
- d. Three-dimensional distribution generator and threshold-value determination circuit.

- a. Structure on the recording side.

Fig. 1 shows a structure on the recording side of one embodiment of the invention. In Fig. 1, a digital video signal in which one sample is quantized with eight bits, for instance, is supplied to an input terminal indicated at 1. The digital video signal is given to a block segmentation circuit 2. Data occurring in the order of television scanning is converted into data in the order of blocks.

At the block segmentation circuit 2, a picture of one frame of (520 lines x 720 picture elements), for example, is segmented into (MxN) blocks as shown

in Fig. 2. One block is selected to have the two-frame size. Each frame is composed of (4 lines x 4 picture elements) as shown in Fig. 3, for instance. Moreover, as shown in Fig. 4, a sub-sampling pattern is made to have an offset between frames by sub-sampling. In Fig. 4, \bigcirc indicates a picture element to be transmitted, and Δ indicates a picture element which is not transmitted. Such sub-sampling pattern enables good interpolation in still areas in the case where the interpolation is carried out for thinned picture elements. The digital video signal converted into in the order of blocks B_{11} , B_{12} , B_{13} B_{MN} is generated from the block segmentation circuit 2.

The output signal of the block segmentation circuit 2 is supplied to a detection circuit 3, a delay circuit 4, and an average circuit 16. The average circuit 16 adds data of picture elements at the same position in two areas included in one block and divides a result of the addition by two to convert an original three-dimensional block into a two-dimensional block. The output signal of the average circuit 16 is given to a detection circuit 17.

The detection circuit 3 detects not only a maximum value MAX3 and a minimum value MIN3 of each block but also a maximum frame difference. The detection circuit 17 detects the maximum value MAX2 and the minimum value MIN2 of the averaged block. As mentioned before, since a block is composed of areas, which belong to two frames, a maximum frame difference ΔF of the two areas is detected. The maximum frame difference ΔF is the maximum value among differences obtained by calculating each difference in data of picture elements at the same position between two areas constituting one block.

The maximum value MAX3, the minimum value MIN3 and the maximum frame difference ΔF from the detection circuit 3 and the MAX2 and MIN2 from the detection circuit 17 are given to a three-dimensional distribution generator 5. The generator 5 calculates the occurrence numbers of dynamic ranges DR2 and DR3 using the maximum frame difference ΔF as a parameter and converts the occurrence numbers of the dynamic ranges into cumulative-type distribution as described later.

A threshold-value determination circuit 6 determines optimum threshold values T1 to T4 and a movement threshold value MTH using a cumulative-type distribution table. The optimum threshold value means that it is a threshold value for coding so that the total bit number per frame of data does not exceed a transmission capacity of a transmission path. The optimum threshold value is obtained using a movement threshold value MTH as a parameter. A ROM 7 is provided in relation to the threshold-value determination circuit 6. A program for obtaining the optimum threshold value is stored

in the ROM 7.

Picture element data PD is fed to a frame-difference detecting circuit 8 through the delay circuit 4. The detecting circuit 8 detects the maximum frame difference ΔF in a manner similar to that of the above-stated detection circuit 3. The maximum frame difference ΔF and the picture element data PD from the frame-difference detecting circuit 8 are supplied to a movement decision circuit 9. The circuit 9 compares the movement threshold value MTH from the threshold-value decision circuit 6 and the maximum frame difference ΔF to decide whether a block to be processed is a moving block or a still block.

A block having a relationship of (the maximum frame difference $\Delta F >$ the movement threshold value MTH) is decided to be a moving block, while a block having a relationship of (the maximum frame difference $\Delta F \leq$ the movement threshold value MTH) is decided to be a still block. Picture element data of the moving block is given to a three-dimensional ADRC encoder 10. Further, picture element data of the still block is supplied to an average circuit 11. In a manner similar to the above-mentioned average circuit 16, the average circuit 11 adds data of picture elements at the same position in two areas included in one block and divides a result of the addition by two to develop a block having picture elements equal to one half of the number of picture elements of the original one block. Such processing is called "frame-dropping processing." The output signal of the average circuit 11 is fed to a two-dimensional ADRC encoder 12. The threshold values T1 to T4 have been supplied to these encoders 10 and 12 from the threshold-value decision circuit 6.

At the three-dimensional ADRC encoder 10, the maximum value MAX3 and the minimum value MIN3 among a total of 32 picture element data of (4 lines x 4 picture elements x 2 frames) can be detected and the dynamic range DR3 can be obtained by ($\text{MAX3} - \text{MIN3} = \text{DR3}$). The bit number of a code signal DT3 is defined by the relationship between the dynamic range DR3 of the block and the threshold value. Namely, in the block of ($\text{DR} \geq \text{T1}$), a four-bit code signal is developed; in the block of ($\text{T1} - 1 \geq \text{DR} \geq \text{T2}$), a three-bit code signal is formed; in the block of ($\text{T2} - 1 \geq \text{DR} \geq \text{T3}$), a two-bit code signal is formed; in the block of ($\text{T3} - 1 \geq \text{DR} \geq \text{T4}$), a one-bit code signal is developed; and in the block of ($\text{T4} - 1 \geq \text{DR} \geq \text{DR minimum value}$), a zero-bit code is given to indicate that no code signal is sent.

For instance, in the case of the coding of four-bit quantization, the dynamic range DR3 detected is divided into 16 ($= 2^4$), and the four-bit code signal DT3 is generated corresponding to the range

to which the level of data belongs after each minimum value MIN of picture element data has been eliminated.

At the two-dimensional ADRC encoder 12, the maximum value MAX2, the minimum value MIN2 and the dynamic range DR2 are detected to develop a code signal DT2 in a manner similar to the above-mentioned three-dimensional ADRC encoder 10. It is to be noted here that the objective of coding is data whose number of picture elements has been reduced to 1/2 by the average circuit 11 at the previous stage.

The output signal (DR3, MIN3, DT3) of the three-dimensional ADRC encoder 10 and the output signal (DR2, MIN2, DT2) of the two-dimensional ADRC encoder 12 are supplied to a selector 13. The selector 13 is controlled by a decision signal SJ from the movement decision circuit 9. That is, the output signal of the three-dimensional ADRC encoder 10 is selected by the selector 13 in the case of a moving block. In the case of a still block, the selector 13 selects the output of the two-dimensional ADRC encoder 12. The output signal of the selector 13 is given to a frame segmentation circuit 14.

In addition to the output signal of the selector 13, a threshold value code Pi for designating the setting of a threshold value and the decision code SJ are given to the frame segmentation circuit 14. The threshold value code Pi varies with two-frame unit, while the decision code SJ changes with one frame unit. The circuit 14 converts an input signal into recording data of frame structure. In the frame segmentation circuit 14, the processing of coding for an error correction code is made when necessary. The recording data obtained at an output terminal 15 of the frame segmentation circuit 14 is given to a rotating head through a recording amplifier, a rotating transformer, etc. and recorded onto a magnetic tape, though not shown.

b. ADRC encoder

Fig. 5 shows a structure of one example of the three-dimensional ADRC encoder 10. In Fig. 5, a maximum-value detecting circuit 22, a minimum-value detecting circuit 23 and a delay circuit 24 are connected to an input terminal 21. A maximum value MAX3 detected by the maximum-value detecting circuit 22 is supplied to a subtraction circuit 25. A minimum value MIN3 detected by the minimum-value detecting circuit 23 is given to the subtraction circuit 25 so that a dynamic range DR3 is provided from the subtraction circuit 25.

Picture element data is supplied to a subtraction circuit 26 through the delay circuit 24. The minimum value MIN3 is given to the subtraction circuit 26. Picture element data PDI reduced by the

minimum value is generated from the circuit 26. The picture element data PDI is supplied to a quantization circuit 29. The dynamic range DR3 is taken out to an output terminal 30 and given to an ROM 27. To the ROM 27 is given the threshold value code Pi generated at the threshold-value determination circuit 6 from a terminal 28. A quantization step Δ and a bit-number code Nb indicative of the bit number are generated from the ROM 27.

The quantization step Δ is supplied to the quantization circuit 29, and a code signal DT3 is developed by the processing of multiplication of the data PDI reduced by the minimum value by the quantization step Δ . The code signal DT3 is taken out at an output terminal 33. Output signals generated at output terminals 30, 31, 32 and 33 are given to the frame segmentation circuit 14. The bit number code Nb is used for selection of effective bits at the circuit 14.

c. Forming a three-dimensional distribution table.

The forming of the three-dimensional distribution table made at the three-dimensional distribution generator 5 will be described with reference to Fig. 6. In Fig. 6, an ordinate indicates the dynamic range DR3, while an abscissa represents the maximum frame difference ΔF . These dynamic range DR3 (= MAX3 - MIN3) and the maximum frame difference ΔF are the ones detected by the detection circuit 3. The dynamic range DR2 (= MAX2 - MIN2) is the one detected by the detection circuit 17. These values MAX3, MIN3, MAX2, MIN2 and ΔF are detected at the same time. The maximum frame difference ΔF can have values of the range (of 0 to 255). However, in this example, all the values equal to or more than 19 are treated as 19 for simplicity as shown in Fig. 6.

For every block, the range of (0 to ΔF) is made to be (+2) as an occurrence number among areas designated by the dynamic range DR3, and the range of ($\Delta F + 1$ to 19) is made to be (+1) as an occurrence number among areas designated by the other dynamic range DR2. The values (+2) and (+1) correspond to the fact that the amount of generated information of the still block is one half of that of the moving block. This processing is done for blocks over a whole picture, for example. When the movement threshold value MTH smaller than the maximum frame difference ΔF is given, the occurrence number of (+2) is allotted to the range of (0 to ΔF), because the blocks are treated as the moving ones. Additionally, when the movement threshold value MTH larger than the maximum frame difference ΔF is supplied, the frequency of (+1) is allotted to the range of ($\Delta F + 1$ to 19) since the blocks are treated as still ones. For example, the block next to the block shown at A of

Fig. 6 has the same dynamic ranges DR3 and DR2, and if they have different maximum frame differences ΔF , the distribution table of A of Fig. 6 changes to that shown at B of Fig. 6 by the addition of information of these blocks. The distribution tables collected and calculated over the whole picture are converted into cumulative-type distribution tables by performing accumulation toward 0 from 255 of the dynamic range DR3 for every value of the maximum frame difference ΔF . The purpose of the conversion into the cumulative type is to easily and immediately obtain the amount of generated information. Fig. 7 is a graph for showing the cumulative-type distribution tables thus obtained with respect to each maximum frame difference.

The threshold-value determination circuit 6 determines a set of the optimum threshold values and the movement threshold value MTH using the cumulative-type distribution tables. This determination is made with the following method. By giving an initial value as the movement threshold value MTH to the extent that no jerkiness is caused in a reproduced picture, the maximum frame difference ΔF selects a predetermined cumulative-type distribution table. In this distribution table, a set of the threshold values are determined by varying the threshold values so that the amount of generated information (total bit number) does not exceed a target value. If the chasing into the target value is impossible, a set of the threshold values are searched once again so that said amount does not exceed the target value by changing the movement threshold value MTH. The processing of determining the set of the threshold values is performed according to the program stored in the ROM 7.

d. An example of the three-dimensional distribution generator and the threshold-value determination circuit.

The three-dimensional distribution generator 5 and the threshold-value determination circuit 6 have the structure shown in Fig. 8 as one example. In this structure, a RAM 46 for a moving block and an RAM 66 for a still block are provided. The separate provision of these RAMs is due to the fact that it is difficult in terms of operation speed to provide the same memory for the RAMs, designate points corresponding to the dynamic ranges DR3 and DR2 and write into one block interval (+2) and (+1).

The structure and operation on the RAM 46 for a moving block will be described.

In Fig. 8, the maximum value MAX3 from an input terminal indicated at 41 and the minimum value MIN3 from an input terminal 42 shown at 42 are supplied to a subtraction circuit 43. The dy-

dynamic range DR3 for a moving block expressed by ($MAX3 - MIN3 = DR3$) is given to an address controller 44. The maximum frame difference ΔF is also given to the controller 44. This controller 44 generates addresses in the horizontal (upper) and vertical (lower) directions with respect to a RAM 46. The RAM 46 has addresses (0 to 255) corresponding to the dynamic range DR3 in the vertical direction and addresses (0 to 19) in the horizontal direction, and all the contents of the memory are cleared in the initial state.

Data read out of the RAM 46 is supplied through a register 53 having an output control function to an addition circuit 47, and the output of the circuit 47 is given via a register 48 to the RAM 46. An address depending on the dynamic range DR3 and the maximum frame difference ΔF is fed to the RAM 46 so that distribution may be stored therein. Clearly, the output data of the RAM 46 is supplied to the addition circuit 47 through the register 53, and the output data of the addition circuit 47 is written into the same address of the RAM 46 through the register 48.

The output data of a (+2) generating circuit 50 is supplied to the addition circuit 47 through a register 49. The (+2) generating circuit 50 produces a value of (+2). In this case, (+2) is written into the range of (0 ~ ΔF) by the address controller 44. A distribution table (refer to Fig. 6) concerning the dynamic range DR3 of a picture (two frames) is developed into the RAM46 by said register 53, the addition circuit 47, the register 48, the (+2) generating circuit 50, etc.

Next, a register 52 and the register 53 are brought to an output-enabling state and a register 49 is brought to an output-unable state, so that a cumulative distribution table can be made. Addresses in the horizontal direction (upper addresses) which are incremented up to 19 starting from 0 of the maximum frame difference ΔF and addresses in the vertical direction (lower addresses) which are decremented by (-1) from 255 in each value of the maximum frame differences ΔF are supplied to the RAM 46.

With each of the addresses, data read out of the RAM 46 is added to previous data stored in the register 52 at the addition circuit 47. Since the output data of the addition circuit 47 is written into the RAM 46 at the same address as the read-out address, the cumulative-type distribution table on the dynamic range DR3 has been stored into the RAM 46 at the time when the addresses have been decremented from 255 to zero.

To perform the calculation of the amount of generated information, the threshold values T1 to T4 in the level direction are supplied sequentially to the RAM 46 as a lower address signal from the address controller 44. An upper address signal is

defined by the maximum frame difference ΔF . In response to the threshold value T1, distribution x_1 is read out of the RAM 46 and given to an addition circuit 56. The output signal of the addition circuit 56 is fed back to the circuit 56 through a register 57 and supplied to a comparison circuit 58.

The threshold value T2 is given to the RAM 46 after the threshold value T1, and ($x_1 + x_2$) is read out from the RAM 46. At the addition circuit 56, the addition with x_1 stored in the register 57 is performed. The added output is stored into the register 57. Next, with the supply of the threshold value T3 to the RAM 46, ($x_1 + x_2 + x_3$) is read out of the RAM 46 and added to ($2x_1 + x_2$) stored in the register 57 at the addition circuit 56. Further, the threshold value T4 is supplied to the RAM 46. Similarly, the output read out from the RAM 46 and the output of the register 57 are added at the circuit 56. As a result, the output of the addition circuit 56 becomes

$$4x_1 + 3x_2 + 2x_3 + 1x_4 .$$

The output of the addition circuit 56 is the amount of generated information corresponding to the threshold values T1 to T4.

With respect to the dynamic range DR2, the structures of the distribution generator and the threshold-value determination circuit on the above-mentioned dynamic range DR3 are provided similarly.

Specifically, an RAM 66 and an address controller 64 are employed. A dynamic range DR2 from a subtraction circuit 63 and a value of ($\Delta F + 1$) obtained by a (+1) generating circuit 65 from a maximum frame difference ΔF are supplied to the address controller 64. The subtraction circuit 63 performs the subtraction of a maximum value MAX2 given from an input terminal 61 and an MIN2 fed from an input terminal 62.

In connection with the RAM 66, an addition circuit 67, registers 68, 69, 72, 73 and 75, and a (+1) generating circuit 70 are provided. The control for the RAM 66 is essentially the same as that of the RAM 46. Here, although +2 is written into the RAM 46 with respect to 0 to ΔF , +1 for developing distribution is written in the range of ($\Delta F + 1$) to 19 in the RAM 66. The output of a register 75 and that of a register 55 are subjected to a wired-OR operation on the output side of the register 75. The amount of generated information supplied to the addition circuit 56 is consequently produced by both of the dynamic range DR3 and the dynamic range DR2.

The comparison circuit 58 becomes "0" when said amount of generated information exceeds a reference value (target value), whereas when the amount of generated information does not exceed

the reference value, it generates a comparison output signal "1". The comparison output signal is supplied to the address controllers 44 and 46. When the comparison output is "1", the address controller 44 stops updating the threshold value and generates on an output terminal 54 a threshold code Pi indicative of the threshold value at that time.

Processing for converting the above-mentioned distribution tables into cumulative type ones and processing for determining the optimum threshold values can be carried out during a vertical blanking period.

With the above-mentioned construction shown in Fig. 8, three-dimensional distribution tables are formed and converted into cumulative-type ones, and the determination of the optimum threshold values are made.

Next, an example a structure of the address controller 44 will be described referring to Fig. 9. In Fig. 9, the maximum value MAX3 and the minimum value MIN3 are given to the input terminals 41 and 42, respectively. The dynamic range DR3 is calculated by a subtraction circuit 43. The dynamic range DR3 is taken out from an output terminal 165 through a register 164 having an output control function. An address generated at the output terminal 165 is the one lying in the vertical (lower) direction of the RAM 46.

Additionally, the output signal of a cumulative counter 166 is taken out at the output terminal 165 through a register 167 having an output control function as an address signal.

Further, each of 168, 169, 170 and 171 indicates a ROM. For example, eleven kinds of threshold values T1 are stored in the ROM 168. To the other ROMs 169, 170 and 171 are similarly stored eleven kinds of threshold values T2, T3 and T4. The threshold value code Pi generated at an address generating circuit 176 is given to the ROMs 168 to 171 as an address.

The output signal of the comparison circuit 58 is supplied to the address generating circuit 176 from a terminal 177. An address which varies at a predetermined period is supplied to the ROMs 168 to 171 during the "0" period. Threshold values are sequentially read out of the ROMs 168 to 171 until the amount of generated information reaches a value equal to or less than a reference value, that is, until the comparison output signal becomes "1". The threshold values read out of the respective ROMs 168 to 171 are taken out at the output terminal 165 through registers 172, 173, 174 and 175 having an output control function. The threshold values are output in that order by the registers 172 to 175.

The threshold value code Pi for designating an optimum threshold value generated at the address

generating circuit 176 is taken out at an output terminal 178. The threshold value code Pi is used for ADRC coding and transmitted.

An address in the horizontal (upper) direction of the RAM 46 is generated at an output terminal 183. The above-mentioned address generated at the output terminal 165 is the one relating to the dynamic range DR3, while the address generated at the output terminal 183 is the one relating to the maximum frame difference ΔF .

181 shows a cumulative counter. An address developed by the cumulative counter 181 is taken out at an output terminal 183 through a register 182 with an output control function. The counter 181 generates an address for forming a distribution table.

Also, a ROM 184 is provided, and the output of the ROM 184 is taken out at the output terminal 183 through a register 185 having an output control function. The output of the address generating circuit 176 is given to the ROM 184. In calculating the amount of generated information, the output signal of the ROM 184 is employed.

The construction of the address controller 64 is similar to that of the address controller 44. Further, in the embodiment of Figs. 1 and 8, MIN, MAX and DR are separately calculated at the two-dimensional and three-dimensional ADRCs to develop accurate distribution tables. However, there may be a case where distribution tables are formed without making any distinction between the two- and three-dimensional ADRCs and threshold values are determined.

Although the frame-difference detecting circuit 8 is provided separately from the detection circuit 3 in Fig. 1, the maximum frame difference ΔF from the detection circuit 3 may be stored so that the decision of movement can be done using the maximum frame difference. Also, the three-dimensional ADRC encoder 10 and the two-dimensional ADRC encoder 12 may have a common circuit construction.

The present invention, which relates to a high efficiency coding apparatus such as variable-length ADRC for a three-dimensional block, employs the movement threshold value, in addition to the dynamic range DR, to keep the amount of generated information less than a target value, taking into the account that the amount of transmitted information is compressed by the frame-dropping processing in still areas. As a result, by varying the movement threshold value, the areas to be treated as still blocks are increased. Therefore, the threshold values in the level direction may not be strict values. The invention enables the reduction of quantization noises of a reproduced picture.

Also, since the invention makes distribution tables taking into consideration that the dynamic

range DR2 of an averaged still block is lowered as compared with an original dynamic range DR3 to reduce the amount of generated information, such amount of generated information can be calculated with high precision.

Claims

1. A high efficiency coding apparatus for coding digital video data in a format composed of blocks of digital video data representing a three-dimensional group of picture elements belonging to a plurality of frames and for allowing video data compression for transmission by data transmission means having a predetermined transmission capacity, said apparatus comprising:

first and second detecting means (22, 23) for detecting maximum (MAX3) and minimum (MIN3) values, respectively, of the digital video data representing the plural picture elements in each of said blocks;

means (25) for generating dynamic range information (DR3) for each said block from said maximum and minimum values for the respective block;

movement detecting means (9) for detecting the amount of movement in each block and for generating a detected amount of movement;

means for generating distribution tables addressed by said dynamic range information and said detected movement amount by, for each block into which a predetermined period of not less than one frame period is divided adding a first number to respective entries in said tables if said detected movement amount is greater than a predetermined movement amount and by adding a second number, less than said first number to respective entries in said tables if said detected movement amount is smaller than said predetermined movement amount;

means (6) for determining an encoding bit number for each block and a threshold value of said movement amount during said predetermined period from said distribution tables and said predetermined transmission capacity of said transmission means;

means (11) for averaging digital data of plural video fields in a block in which said detected amount of movement is less than said threshold value to produce a two dimensional block;

encoding means (10, 12) for encoding the digital video data using a number of bits equal to said encoding bit number for each datum in a block; and

means (14) for transmitting the output of said encoding means, a first additional code for each block formed of at least two of said maximum value, minimum value and a signal based on said dynamic range information and a signal based on the detected amount of movement, and a second additional code for each said predetermined period.

2. A high efficiency coding apparatus as claimed in claim 1, wherein said encoding means includes first (12) and second (10) encoding means for two-dimensional and three-dimensional blocks, respectively, wherein output data of said averaging means (11) is supplied to said first encoding means, and said encoder means further includes selector means (13) for selecting one of the outputs of said first and second encoding means.
3. A high efficiency coding apparatus as claimed in claim 2, wherein said encoding means includes comparator means (9) for comparing the detected amount of movement for each block and the threshold value, and the output of said comparator means controls said selector means.
4. A high efficiency coding apparatus as claimed in claim 1, 2 or 3, wherein said movement detecting means (4) includes first comparators each for comparing digital data of a picture element in a first video frame with digital data of a corresponding picture element in a second video frame, and selecting means for selecting biggest one of the outputs of said first comparators and generating the detected amount of movement.
5. A high efficiency coding apparatus as claimed in claim 1, 2, 3 or 4 wherein said means for determining (6) includes calculating means (56, 57) for calculating the total bit number required to code the data for said predetermined period using said distribution tables and comparator means (58) for comparing said total bit number with said predetermined transmission capacity of said data transmission means.
6. A high efficiency coding apparatus as claimed in claim 5, wherein said means for generating (5) includes first generating means for generating first distribution tables of said dynamic range information, and second generating means for generating second distribution tables of the integrating type from said first distribution tables, wherein an entry of said second tables is equal to the sum of the cor-

responding and previous entries of said first tables.

Patentansprüche

1. Codiervorrichtung mit hoher Wirksamkeit zur Codierung digitaler Videodaten in einem Format, welches aus Blöcken von digitalen Videodaten besteht, die eine dreidimensionale Gruppe von Bildelementen darstellen, welche zu einer Vielzahl von Datenrahmen gehören, und zur Ermöglichung einer Komprimierung der Videodaten zur Übertragung mittels einer Datenübertragungseinrichtung mit einer vorgegebenen Übertragungskapazität, wobei die Vorrichtung umfaßt:
 erste und zweite Detektionsmittel (22, 23) zur jeweiligen Feststellung von Maximal-(MAX3) und Minimal-(MIN3) Werten der digitalen Videodaten, welche die Mehrfachbildelemente in jedem der Blöcke darstellen;
 Mittel (25) zur Erzeugung einer dynamischen Bereichsinformation (DR3) für jeden Block aus den Maximal- und Minimalwerten für den jeweiligen Block;
 Bewegungsfeststellungsmittel (9) zur Feststellung des Bewegungsbetrags in jedem Block und zur Erzeugung eines festgestellten Bewegungsbetrags;
 Mittel zur Erzeugung von Verteilungstabellen, welche durch die dynamische Bereichsinformation und den festgestellten Bewegungsbetrag für jeden Block, in welchen eine vorgegebene Periode von nicht weniger als eine Datenrahmenperiode aufgeteilt ist, durch Hinzufügen einer ersten Anzahl von jeweiligen Eintragungen in die Tabellen, wenn der festgestellte Bewegungsbetrag größer als ein vorgegebener Bewegungsbetrag ist, und durch Hinzufügen einer zweiten Anzahl, die kleiner als die erste Anzahl ist, zu den jeweiligen Eintragungen in den Tabellen, wenn der festgestellte Bewegungsbetrag kleiner als der vorgegebene Bewegungsbetrag ist, adressiert werden;
 Mittel (6) zur Bestimmung einer Anzahl von Codierbits für jeden Block und eines Schwellwertes des Bewegungsbetrags während der vorgegebenen Periode von den Verteilungstabellen und der vorgegebenen Übertragungskapazität der Übertragungseinrichtung;
 Mittel (11) zur Mittelwertbildung der digitalen Daten der Mehrfachvideofelder in einem Block, in welchem der festgestellte Bewegungsbetrag kleiner als der Schwellwert ist, um einen zweidimensionalen Block zu erzeugen;
 Codiermittel (10, 12) zur Codierung der digitalen Videodaten unter Verwendung einer Anzahl von Bits, welche gleich der Anzahl der Codier-

bits für jedes Datenelement in einem Block ist; und

- Mittel (14) zur Übertragung des Ausgangssignals der Codiermittel, wobei ein erster zusätzlicher Code für jeden Block aus mindestens zwei Werten des Maximalwerts, des Minimalwerts und eines Signals, das auf der Grundlage der dynamischen Bereichsinformation basiert, und eines Signals, das auf dem festgestellten Bewegungsbetrag basiert, und ein zweiter zusätzlicher Code für jede vorgegebene Periode ausgebildet werden.
2. Codiervorrichtung mit hoher Wirksamkeit nach Anspruch 1, bei der die Codiereinrichtung jeweils erste (12) und zweite (10) Codiermittel für zweidimensionale und dreidimensionale Blöcke enthält, bei der die Ausgangsdaten der Mittel (11) zur Mittelwertbildung den ersten Codiermitteln zugeführt werden, und die Codiereinrichtung weiterhin eine Selektoreinrichtung (13) zur Auswahl eines der Ausgangssignale der ersten und zweiten Codiermittel enthält.
3. Codiervorrichtung mit hoher Wirksamkeit nach Anspruch 2, bei der die Codiereinrichtung Vergleichsmittel (9) zum Vergleich des festgestellten Bewegungsbetrags für jeden Block und des Schwellwertes enthalten, und bei der das Ausgangssignal der Vergleichsmittel die Selektoreinrichtung steuert.
4. Codiervorrichtung mit hoher Wirksamkeit nach Anspruch 1, 2 oder 3, bei der die Bewegungsfeststellungseinrichtung (4) erste Vergleiche, von denen jeder zum Vergleich digitaler Daten eines Bildelements in einem ersten Videodatenrahmen mit digitalen Daten eines entsprechenden Bildelements in einem zweiten Videodatenrahmen dient, und Auswahlmittel zur Auswahl des größten der Ausgangssignale der ersten Vergleiche und zur Erzeugung des festgestellten Bewegungsbetrags enthält.
5. Codiervorrichtung mit hoher Wirksamkeit nach Anspruch 1, 2, 3 oder 4, bei der die Mittel (6) zur Bestimmung Berechnungsmittel (56, 57) zur Berechnung der gesamten Bitanzahl, die erforderlich ist, die Daten für die vorgegebene Periode unter Verwendung der Verteilungstabellen zu codieren, und Vergleichsmittel (58) zum Vergleich der Gesamtanzahl der Bits mit der vorgegebenen Übertragungskapazität der Übertragungseinrichtung enthalten.
6. Codiervorrichtung mit hoher Wirksamkeit nach Anspruch 5, bei der die Erzeugungseinrichtung (5) erste Erzeugungsmittel zur Erzeugung von

ersten Verteilungstabellen der dynamischen Bereichsinformation und zweite Erzeugungsmittel zur Erzeugung von zweiten Verteilungstabellen des integrierten Typs aus den ersten Verteilungstabellen enthält, bei der ein Eintrag der zweiten Tabellen gleich ist der Summe der entsprechenden und vorherigen Eintragungen der ersten Tabellen.

Revendications

1. Dispositif de codage à rendement élevé pour coder des données numériques vidéo dans un format composé de blocs de données numériques vidéo représentant un groupe tridimensionnel d'éléments d'image appartenant à une pluralité de trames et pour permettre la compression des données vidéo pour une transmission par un moyen de transmission de données ayant une capacité de transmission prédéterminée, ledit dispositif comprenant :

des premier et deuxième moyens détecteurs (22, 23) pour détecter respectivement des valeurs maximale (MAX3) et minimale (MIN3) des données numériques vidéo représentant l'ensemble des éléments d'image dans chacun desdits blocs ;

un moyen (25) pour générer des informations de plage dynamique (DR3) pour chaque dit bloc à partir desdites valeurs maximale et minimale pour le bloc respectif ;

un moyen détecteur de transfert (9) pour détecter la quantité de transfert dans chaque bloc et pour générer une quantité de transfert détectée ;

un moyen pour générer des tables de répartition adressées par lesdites informations de plage dynamique et ladite quantité de transfert détectée, pour chaque bloc en lequel est divisée une période prédéterminée non inférieure à une période de trame, en ajoutant un premier nombre aux éléments respectifs desdites tables si ladite quantité de transfert détectée est supérieure à une quantité de transfert prédéterminée et en ajoutant un second nombre, inférieur audit premier nombre, aux éléments respectifs desdites tables si ladite quantité de transfert détectée est inférieure à ladite quantité de transfert prédéterminée ;

un moyen (6) pour déterminer un nombre de bits de codage pour chaque bloc et une valeur de seuil de ladite quantité de transfert pendant ladite période prédéterminée à partir desdites tables de répartition et de ladite capacité de transmission prédéterminée dudit moyen de transmission ;

un moyen (11) pour calculer la moyenne des données numériques de l'ensemble des

trames vidéo dans un bloc dans lequel ladite quantité de transfert détectée est inférieure à ladite valeur de seuil afin de produire un bloc bidimensionnel ;

un moyen codeur (10, 12) pour coder les données numériques vidéo en utilisant un nombre de bits égal audit nombre de bits de codage pour chaque donnée dans un bloc ; et,

un moyen (14) pour transmettre le signal de sortie dudit moyen codeur, un premier code supplémentaire pour chaque bloc composé d'au moins deux de ladite valeur maximale, ladite valeur minimale et un signal dépendant desdites informations de plage dynamique et un signal dépendant de la quantité de transfert détectée, et un second code supplémentaire pendant chaque dite période prédéterminée.

2. Dispositif de codage à rendement élevé selon la revendication 1, dans lequel ledit moyen codeur inclut des premier (12) et second moyen codeur (10) respectivement pour des blocs bidimensionnels et tridimensionnels, où les données de sortie dudit moyen de calcul de la moyenne (11) sont fournies audit premier moyen codeur, et ledit moyen codeur inclut en outre un moyen sélecteur (13) pour sélectionner un des signaux de sortie desdits premier et second moyens codeurs.

3. Dispositif de codage à rendement élevé selon la revendication 2, dans lequel ledit moyen codeur inclut un moyen comparateur (9) pour comparer la quantité de transfert détectée pour chaque bloc et la valeur de seuil, et le signal de sortie dudit moyen comparateur commande ledit moyen sélecteur.

4. Dispositif de codage à rendement élevé selon l'une quelconque des revendications 1 à 3, dans lequel ledit moyen détecteur de transfert (4) inclut des premiers comparateurs chacun pour comparer les données numériques d'un élément d'image dans une première trame vidéo aux données numériques d'un élément d'image correspondant dans une deuxième trame vidéo, et un moyen sélecteur pour sélectionner le plus grand des signaux de sortie desdits premiers comparateurs et générer la quantité de transfert détectée.

5. Dispositif de codage à rendement élevé selon l'une quelconque des revendications 1 à 4, dans lequel ledit moyen de détermination (6) inclut un moyen de calcul (56, 57) pour calculer le nombre total de bits nécessaires pour coder les données pendant ladite période prédéterminée en utilisant lesdites tables de ré-

partition et un moyen comparateur (58) pour comparer ledit nombre total de bits à ladite capacité de transmission prédéterminée dudit moyen de transmission de données.

- 5
6. Dispositif de codage à rendement élevé selon la revendication 5, dans lequel ledit moyen générateur (5) inclut un premier moyen générateur pour générer des premières tables de répartition desdites informations de plage dynamique, et un second moyen générateur pour générer des secondes tables de répartition du type à intégration à partir desdites premières tables de répartition, où un élément desdites secondes tables est égal à la somme des éléments correspondant et précédent desdites premières tables.
- 10
- 15

20

25

30

35

40

45

50

55

Fig. 1




Fig. 2

B_{11}	B_{12}					B_{1M}
B_{21}	B_{22}					B_{2M}
B_{N1}						B_{NM}

Fig. 3




Fig. 4




Fig. 5




Fig. 6A MAXIMUM FRAME DIFFERENCE IN A BLOCK




Fig. 6B MAXIMUM FRAME DIFFERENCE IN A BLOCK




Fig. 7




Fig. 10





Fig. 8



MONITOR CAMERA SYSTEM

Patent number: JP9247654
Publication date: 1997-09-19
Inventor: NAKADA TOMOYUKI
Applicant: FUJITSU GENERAL LTD
Classification:
International: H04N7/18; H04N7/18; (IPC1-7): H04N7/18
European:
Application number: JP19960049713 19960307
Priority number(s): JP19960049713 19960307

Report a data error here

Abstract of JP9247654

PROBLEM TO BE SOLVED: To provide the technology displaying smoothly a motion of an object image to be monitored when the object image is moved. **SOLUTION:** An image processing section 2 of a transmission section applies band compression to an output video signal S1 of a camera 1 and a data transmission section 3 transmits the resulting video signal to a reception section as a transmission line signal S2. A data reception section 6 of a reception section decodes the signal, an image processing section 7 expands the band and the result is displayed on a video monitor 8 and monitored. A control section 5 of the transmission section controls the image processing section 2 based on motion information S3 from a motion detection section 4 to increase the band compression rate of the video signal when the motion quantity S3 is high thereby increasing the frame frequency and making the frequency band of the transmission line signal S2 constant. Simultaneously band compression information S4 is sent to the reception section as the transmission line signal S2 through time division superimposition or the like with the video signal. The data reception section 6 of the reception section separates the band compression information S4 and a control section 9 conducts the band expansion processing in response to the band compression information S4.

